

FUD-P3/Q3

3P3W Active And Reactive Power Transducer

FUD-P3/Q3 3P3W active reactive power transducer can be customized for multi-power-combined transducer of current, voltage, power and all power measurement in 3P3W, support RS485 port. It adopted SCM technique; excellent stability. Delivering the direction of measured power accurately, applicable for active/reactive power measurement in 3P3W.



Features

1. 3P3W active power transducer
2. 3P3W reactive power transducer
3. Accuracy class can be reach 0.2%
4. Adopted SCM technique; excellent stability
5. Applicable for 3P3W active/reactive power measurement

Parameters

Technical Index	
Standard	GB/T 13850-1998, IEC688:1992
Accuracy	0.2%, 0.5%
Consumption	≤5VA
Accuracy drift	Annual variation <0.2%
Insulation voltage	AC 2kV/min.1mA (Between input-output/power)
Insulation resistance	≥20MΩ (DC500V)
Surge voltage	5KV (Peak value), 1.2/50μs
Response time	≤350ms
Input range	AC 0-5A ,AC 0-500V(Option), 50/60Hz
Absorbed power	Per phase voltage: ≤0.5VA/100V Per phase current: <0.1VA/5A
Overload	Current: 2 times continuous, 30 times/1s;
Load resistance	Current output: RL ≤650Ω Voltage output: RL ≥2kΩ
Working environment	Temperature: -10 to +50°C RH: 20-90%, without condensation

Technical Index

Storage conditions	Temperature: -40 to +70°C
	RH: 20-95%, without condensation
Installation	35mm DIN sliding-way or M4 screws
Dimension	110mm x 75mm x 120mm

Model Description

FUD-Type-Input-Power Supply-Output

Type	P3: 3P3W active power transducer Q3: 3P3W reactive power transducer PQ3: 3P3W active and reactive power transducer
AC input	V1: 100V, V2: 0-220V, V3: 270V, V4: 400V A1: 0-1A, A2: 0-5A.
Power supply	P1: AC110V±10%, P2: AC220V±15%, P3: AC110V-330V.
DC output	O1: 0-20mA, O2: 0-±20mA, O3: 4-20mA, O4: 4-12-20mA, O5: 0-1V, O6: 0-±1V, O7: 0-5V, O8: 0-±5V, O9: RS485.

Example 1: FUD-P3-V1-A2-P2-O8

FUD series 3P3W active power transducer	Input: AC100V, ±5A, ±866W Power supply: AC220V±15% Output: DC0-±5V
---	--

Example 2: FUD-PQ3-V1-A2-P2-O8

FUD series 3P3W active and reactive power transducer	Input: AC100V, ±5A, ±866W(var) Power supply: AC220V±15% Output: DC0-±5V
--	---

Please check the type, input range, output range and power supply when your order the product.